VDM-4050 Web API

Description	api format	Example	Response
Trigger preset	GET /api/presets/:id/exec	GET /api/presets/20/exec	status: 200 {data: 'ok'}
Set the zoom area	POST /api/tasks/exec {tx: int, rx: [int], groups: [int], position: [int, int, int, int], type: 'part'}	{tx:5, rx:[], groups:[], position:[2359,1781,7282,6712], type: 'part'}	status: 200 {data: 'ok'}
List all presets	GET /api/presets		status: 200 [{preserUid: int, name: string }]
Login	POST /api/auth/login {username: string, password: string}	{username: 'admin', password: '1234'}	status: 200 {data: 'ok'}
List all TXs & RXs	GET /api/devices/		status: 200 [{"deviceUid": int, "deviceId": string, "name": string, "type": ENUM(rx, tx), "address": string, "status": string, "online": ENUM(false, true), "source": string, "area": []}]
Matrix	POST /api/devices/setrxsrc {"rxAddress": "rx address", "rxSource" : null or "tx address"}	{"rxAddress": "192.168.1.102", "rxSource" : null or "tx address", }	Success: 200 Fail: 400, {"message": error.message}