WMP-1206

Speaker Circuit Zone Selector



Product Features

- Features 12 individual zone broadcasting buttons, each supporting loads over 300W.
- Equipped with one programmable group zone broadcasting button.
- Includes one master activation button for broadcasting across all zones.
- Each button is equipped with an indicator light.
- Groups can be set and modified at any time.
- Zone activation uses a relay connection method, designed with circuitry to prevent crosstalk between loops.
- Compatible with RS-232 connection to a PC, integrating with BXB graphical control software or other environmental control systems (AMX or Crestron).
- Features controlled input activation for remote triggering.
- Equipped with output control for remote triggering.

Specifications

Product Specifications	
Function Keys	Zone circuit switches x 12; Group switch button x 1; Master switch button x 1
Indicators	Zone circuit switch indicators x 12; Master on/off indicator x 1
Ports	Zone speaker ports x 12; Background music port x 1; RS-232 port x 1; RS-485 port x 1; Link control identification dial switch x 1; External start dry contact x 1; Start dry contact x 1

Product Specifications	
Dimensions (WHD)	431 x 94 x 225 mm (without terminals)
Power Supply	AC 110~240 50-60Hz

BXB
ADD 6F-1, No.288-5, Xinya Rd., Qianzhen Dist., Kaohsiung City 806604, Taiwan
TEL +886 7 9703838
FAX +886 7 9703883
MAIL bxb@bxb.tw
WEB www.bxbsystem.com