WS-817ALM

Amplifier Teaching Wall Speaker





Product Features

- It can become Teaching Amplifiers System by using pre - mixer and amplifier device inside the speaker.
- With micro-computer PA main controller, you can do the Area Broadcasting / Intercom functions by the remote decoder inside the speaker.
- Auto ON/OFF: When there is sound input it will be turned on automatically; if there is no sound input for 60 seconds it will be switched off automatically.
- Put two speaker's units into single box for better sound quality and increasing sound pressure.
- Speaker unit: coaxial two way, low 6.5" high 2“ x2
- The material of its box is ABS (Fire-Resistant). One-body shape with fashion style and ivory-white color make it easily fit into the environment decoration.

BXB
ADD 6F-1, No.288-5, Xinya Rd., Qianzhen Dist., Kaohsiung City 806604, Taiwan
TEL +886 7 9703838
FAX +886 7 9703883
MAIL bxb@bxb.tw
WEB www.bxbsystem.com

Product Specifications	
Model	**WS-817ALM Amplifier Teaching Wall Speaker**
Speaker unit	6.5" × 2
Rated Input	35W
Input impedance	100V：3W (3.3KΩ)、6W (1.7KΩ)、10W (1KΩ)
S.P.L	94 ~ 105dB
Frequency response	80 - 15KHz
Box Material	ABS
Dimension	350 x 160 x 250 mm
Weight	2.8kg
Installation method	Wall-mounted

BXB
ADD 6F-1, No.288-5, Xinya Rd., Qianzhen Dist., Kaohsiung City 806604, Taiwan
TEL +886 7 9703838
FAX +886 7 9703883
MAIL bxb@bxb.tw
WEB www.bxbsystem.com